

LCD repeater with emulator functions

FR2000

FP1200 / FP2000 series

A powerful LCD repeater that can be used as a local or global repeater on a FP1200 / FP2000 fire panel network. Fire panels can be emulated from the FR2000. An 80 x 40 backlit graphic display and full indication and control keyboard is provided standard.

Specifications

Supply voltage	230 V ac (+10/-15%)
	50 Hz
	50 VA
Min. supply current @ 24 V dc	0.15 A
Battery charger rating @ 27.6 V dc	0.3 A
Total supply rating @ 27.6 V dc	1 A
Relay rating @ 24 V dc	2 A
Weight (no batteries)	7.5 kg
Dimensions (mm H x W x D)	365 x 444 x 111

Ordering Information

FR2000	LCD repeater with emulator functions
NE2011	RS485 network extension board
NE2051	Fibre optic network extension board
FP-RIM1270	Rim surround for the 780 and 1200N series fire panel boxes



- 8 x 40 character graphic display
- Arcnet network connection to FP1200/FP2000 series firepanels
- Global repeater function
- Comprehensive control and display functions
- Fire panel emulation function
- Dual RS232 ports